

CTC-968P Voice & Digital Communications Panel

Seamless Security and Multidimensional Flexibility

CTC-968P is a Security Alarm Control Panel with built-in PSTN and GSM communicators that provide voice and digital services. This system integrates a GSM box to establish an additional wireless communication path that ensures security is never compromised even when the phone line is tampered with.

CTC-968P supports 40 zones to protect your entire premises and uses Code Encryption to deliver infallible signal transmissions between sensors/devices and the Control Panel. This system not only introduces an intelligent and reliable security network to bring you peace of mind but also offers multiple advanced features for operational flexibility and convenience. The Panel can save up to 10 numbers for reporting via various communication channels to different destinations. Its Plug & Play system and multilingual LCD text display/recordings also create a user-friendly interface that features simplicity and adjustability. CTC-968P makes security complete and easy for you by bringing together top solutions in this All-in-One system.



Features:

- Up to 40 zones
- Built-in voice and digital dialers
- Integrated PSTN and GSM communicators
- Alarm reporting paths: Contact ID via PSTN/GSM/SMS text messages to the Central Monitoring Station (CMS); SMS text messages and voice messages to the user
- User-friendly Plug & Play system
- Multilingual text display and pre-recorded alarm messages (up to 4 languages of your choice or standard built-in English/German/French/Italian)
- Up to 10 numbers can be saved: 2 for digital reporting to the CMS, 2 for digital reporting via SMS text messages to the CMS, 2 for SMS text messages to mobile phones, 4 for voice reporting
- 10 user codes (6 User PIN Codes, Installer Code, Master Code, Duress Code and Temporary Code)
- SMS editing: 56 characters in total (14 characters x 4 lines)
- One recordable address message (10 secs max.) for voice reporting and 4 pre-stored alarm messages (Burglary, Fire, Emergency and Panic)
- Remote arming and disarming via DTMF commands
- LCD Display of 16x2 backlit characters and a 16-button backlit keypad
- Each zone can be individually programmed into different zone types with specific device attributes.
- Built-in transmitter to activate Outdoor Bell Box or Wireless Siren
- Full supervision to ensure problem-free operation of the system
- Call acknowledgment by the recipient ensures calls are well received.
- Door open/close monitoring before system arming adds extra caution.
- Tamper detection to protect the unit from unauthorized opening and removal
- Compatible with PIR Motion Detector, Pet Immune PIR Motion Detector, Door Contact, Remote Controller, Remote Keypad, Fixed Panic Button, Night Switch, Smoke Detector, Water Sensor, Indoor Siren, Outdoor Siren, Repeater, External PIR Motion Detector, and Tag Reader

Specifications:

- Power: 12V 1A switching power
- Backup battery: 600mAh Ni-MH rechargeable battery
- Battery backup time: 6 hours minimum
- Alarm output: 105dB @ 1M
- Available frequencies: 433MHz/868.35MHz
- Frequency ranges: 433MHz/868.35MHz: Over 200 meters in open space
- Operating temperature: -10°C to +50°C
- Operating humidity: Up to 85% non-condensing
- Dimensions: 245mm x 180mm x 46mm