

## KP-15 Remote Keypad

## Security at Your Fingertips



- Easy arming/disarming of a security system
- Quick activation of panic, fire, and medical alarms
- 16 soft-touch illuminated keys
- Visual and audible feedback
- Extensive RF range
- Long battery life

The KP-15 Series' remote keypads are useful add-ons to a security system that enable the user to conveniently operate the control panel from easily accessible locations in the home. In addition to allowing the user to arm, partially arm, or disarm the security system with a few button presses, the KP-15 also facilitates quick activation of panic, fire, and medical alarms in the event of emergencies.

The keypad's 16 soft-touch illuminated keys, including 12 operational keys and 4 special function keys labeled with intuitive icons, enhance ease of use and nighttime visibility. Designed to deliver the utmost convenience and peace of mind, the KP-15 further provides three color LED indicators to display system modes as well as audible notifications of successful operations and wrong entries.

The series' KP-15-F1 model, which adopts Climax's latest RF technology, features long RF range, fast signal transmission, and more than six years of battery life. The KP-15-F1 model is compatible with Climax's F1 control panels.

The power-saving function of the KP-15 Series preserves battery life. This series' keypads automatically report low battery status and tampering to the control panel to ensure the devices' proper operation.

The wall-mounted KP-15 Series is waterproof to IP44 standard. The keypads' sleek white or deep gray consoles blend naturally with any home décor.

### Features

- Provides convenient operation of the security system from an easily accessible location in the home
- Easy operation arms, partially arms, or disarms the security system
- Quick activation of panic, fire, and medical alarms
- 16 soft-touch illuminated keys enhance ease of use and nighttime visibility
- LED indicators display system modes
- Audible notifications of successful operations and wrong entries
- Long battery life
- Long RF range and fast signal transmission (KP-15-F1 only)
- Compatible with F1 control panels (KP-15-F1 only)
- Power-saving feature preserves battery life
- Automatically reports low battery status and tampering to the control panel
- Easy programming
- Wall-mounted
- Waterproof to IP44 standard
- White or deep gray console blends naturally with any home décor
- CE compliance

## KP-15 Remote Keypad

### Specifications

#### KP-15-F1

Power source	CR2450 3V lithium battery x 1
Battery life*	6.45 years
Available frequencies	868.6375MHz
Operating temperature	-10°C to +45°C
Operating humidity	Up to 85% non-condensing
Dimensions	103mm x 72mm x 18mm

#### KP-15

Power source	CR2450 3V lithium battery x 1
Battery life*	6 years
Available frequencies	868.6375MHz/433MHz
Operating temperature	-10°C to +45°C
Operating humidity	Up to 85% non-condensing
Dimensions	103mm x 72mm x 18mm

\*Note: Battery life varies by use and configuration.

### Ordering Information

**KP-15-F1** Long RF range and compatibility with Climax's F1 control panels

**KP-15** Compatibility with Climax's standard control panels