

SR-15 Wireless Indoor Siren

Stay Alert to
Protect Your Premises



- Siren output level is 102dB at 1 meter
- Entry and exit delay beeps
- Unique alarm sounds for burglary/panic and fire/water

SR-15 is battery-powered wireless indoor siren. With a siren output level of 102dB at 1 meter, SR-15 activates different alarm sounds for fire and intrusion to audibly inform the users of the type of danger at hand.

SR-15 provides programmable alarm duration of 3, 5 or 10 minutes. If your control panel is distant from the front door and you have difficulty hearing its entry and exit delay beeps, SR-15 can serve as a useful reminder. It can be configured to emit entry and exit delay beeps that urge you to disarm your security system or leave quickly.

SR-15 transmits low battery and supervisory signals to ensure its proper operation. Its cover tamper protection prevents unauthorized removal or sabotage. This wireless siren can be flexibly installed on premises for commercial or residential use and provide effective warnings and reminders for the user.

Features

- Siren output level is 102dB at 1 meter
- Programmable alarm duration of 3/5/10 minutes
- Previous alarm warning indicates the alarms reported while users are away
- Randomized supervision signals to check system integrity
- Unique alarm sounds for burglary/panic and fire/water
- Tamper protection prevents unauthorized removal or sabotage
- Low battery detection
- Easy and flexible installation

Specifications

SR-15-F1

Frequency	433 MHz / 868 MHz
Power Source	Alkaline D batteries x 4
Battery life	3.6 years*
Siren Output	102dB @ 1 meter
Operating Temperature	-10°C to 45°C (14°F to 113°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	228 mm x 113 mm x 54 mm

SR-15 Wireless Indoor Siren**SR-15**

Frequency	433 MHz / 868 MHz
Power Source	Alkaline D batteries x 4
Battery life	2 years*
Siren Output	102dB @ 1 meter
Operating Temperature	-10°C to 45°C (14°F to 113°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	228 mm x 113 mm x 54 mm

**Note: Actual battery life may vary with product settings, operating environment, and usage.*